



For innovation

US 10/657,117

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation and Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents held on the international application filed on **06 March 2002** under the Patent Cooperation Treaty at the UK Receiving Office. The application was allocated the number **PCT/GB2002/000987**.


In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or the inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Under the Companies Act does not constitute a new legal entity but merely
the company to certain additional company law rules.

Signed

Date: 29 June 2006



Home
copy

PCT

REQUEST

The undersigned requests that the present international application be processed according to the Patent Cooperation Treaty.

For receiving Office use only	
PCT/GB 02 / 00987	
International Application No.	
06 MARCH 2002	06.03.2002
International Filing Date	
United Kingdom Patent Office PCT International Application	
Name of receiving Office and "PCT International Application"	
Applicant's or agent's file reference (if desired) (12 characters maximum)	P.Q. 12,931

Box No. I TITLE OF INVENTION	
A METHOD OF MODIFYING LOW FREQUENCY COMPONENTS OF A DIGITAL AUDIO SIGNAL	
Box No. II APPLICANT <input type="checkbox"/> This person is also inventor	
Name and address: (Family name followed by given name; for a legal entity, full official designation. The address must include postal code and name of country. The country of the address indicated in this Box is the applicant's State (that is, country) of residence if no State of residence is indicated below.)	Telephone No. 020 8848 9779
Central Research Laboratories Limited Dawley Road Hayes Middlesex UB3 1HH GB	Facsimile No. 020 8848 6469
	Teleprinter No.
	Applicant's registration No. with the Office
State (that is, country) of nationality: GB	State (that is, country) of residence: GB
This person is applicant for the purposes of: <input type="checkbox"/> all designated States <input checked="" type="checkbox"/> all designated States except the United States of America <input type="checkbox"/> the United States of America only <input type="checkbox"/> the States indicated in the Supplemental Box	
Box No. III FURTHER APPLICANT(S) AND/OR (FURTHER) INVENTOR(S)	
Name and address: (Family name followed by given name; for a legal entity, full official designation. The address must include postal code and name of country. The country of the address indicated in this Box is the applicant's State (that is, country) of residence if no State of residence is indicated below.)	This person is:
LITTLE MAX ANDREW 18 Granby Gardens Reading Berks RG1 5RT GB	<input type="checkbox"/> applicant only <input checked="" type="checkbox"/> applicant and inventor <input type="checkbox"/> inventor only (If this check-box is marked, do not fill in below.)
	Applicant's registration No. with the Office
State (that is, country) of nationality: GB	State (that is, country) of residence: GB
This person is applicant for the purposes of: <input type="checkbox"/> all designated States <input type="checkbox"/> all designated States except the United States of America <input checked="" type="checkbox"/> the United States of America only <input type="checkbox"/> the States indicated in the Supplemental Box	
<input type="checkbox"/> Further applicants and/or (further) inventors are indicated on a continuation sheet.	
Box No. IV AGENT OR COMMON REPRESENTATIVE; OR ADDRESS FOR CORRESPONDENCE	
The person identified below is hereby/has been appointed to act on behalf of the applicant(s) before the competent International Authorities as: <input checked="" type="checkbox"/> agent <input type="checkbox"/> common representative	
Name and address: (Family name followed by given name; for a legal entity, full official designation. The address must include postal code and name of country.)	Telephone No. 020 8848 6490
SHARP ALAN COOPER QED I.P. Services Limited Dawley Road Hayes Middlesex UB3 1HH GB	Facsimile No. 020 8848 6469
	Teleprinter No.
	Agent's registration No. with the Office
<input type="checkbox"/> Address for correspondence: Mark this check-box where no agent or common representative is/has been appointed and the space above is used instead to indicate a special address to which correspondence should be sent.	

Box No.V DESIGNATION OF STATES

Mark the applicable check-boxes below; at least one must be marked.

The following designations are hereby made under Rule 4.9(a):

Regional Patent

- ☐ AP ARIPO Patent: GH Ghana, GM Gambia, KE Kenya, LS Lesotho, MW Malawi, MZ Mozambique, SD Sudan, SL Sierra Leone, SZ Swaziland, TZ United Republic of Tanzania, UG Uganda, ZW Zimbabwe, and any other State which is a Contracting State of the Harare Protocol and of the PCT
- ☐ EA Eurasian Patent: AM Armenia, AZ Azerbaijan, BY Belarus, KG Kyrgyzstan, KZ Kazakhstan, MD Republic of Moldova, RU Russian Federation, TJ Tajikistan, TM Turkmenistan, and any other State which is a Contracting State of the Eurasian Patent Convention and of the PCT
- ☒ EP European Patent: AT Austria, BE Belgium, CH & LI Switzerland and Liechtenstein, CY Cyprus, DE Germany, DK Denmark, ES Spain, FI Finland, FR France, GB United Kingdom, GR Greece, IE Ireland, IT Italy, LU Luxembourg, MC Monaco, NL Netherlands, PT Portugal, SE Sweden, TR Turkey, and any other State which is a Contracting State of the European Patent Convention and of the PCT
- ☐ OA OAPI Patent: BF Burkina Faso, BJ Benin, CF Central African Republic, CG Congo, CI Côte d'Ivoire, CM Cameroon, GA Gabon, GN Guinea, GW Guinea-Bissau, ML Mali, MR Mauritania, NE Niger, SN Senegal, TD Chad, TG Togo, and any other State which is a member State of OAPI and a Contracting State of the PCT (if other kind of protection or treatment desired, specify on dotted line)

National Patent (if other kind of protection or treatment desired, specify on dotted line):

- | | | |
|--|---|---|
| <input type="checkbox"/> AE United Arab Emirates | <input type="checkbox"/> GE Georgia | <input type="checkbox"/> MW Malawi |
| <input type="checkbox"/> AG Antigua and Barbuda | <input type="checkbox"/> GH Ghana | <input type="checkbox"/> MX Mexico |
| <input type="checkbox"/> AL Albania | <input type="checkbox"/> GM Gambia | <input type="checkbox"/> MZ Mozambique |
| <input type="checkbox"/> AM Armenia | <input type="checkbox"/> HR Croatia | <input type="checkbox"/> NO Norway |
| <input type="checkbox"/> AT Austria | <input type="checkbox"/> HU Hungary | <input type="checkbox"/> NZ New Zealand |
| <input type="checkbox"/> AU Australia | <input type="checkbox"/> ID Indonesia | <input type="checkbox"/> PL Poland |
| <input type="checkbox"/> AZ Azerbaijan | <input type="checkbox"/> IL Israel | <input type="checkbox"/> PT Portugal |
| <input type="checkbox"/> BA Bosnia and Herzegovina | <input type="checkbox"/> IN India | <input type="checkbox"/> RO Romania |
| | <input type="checkbox"/> IS Iceland | <input type="checkbox"/> RU Russian Federation |
| <input type="checkbox"/> BB Barbados | <input type="checkbox"/> JP Japan | |
| <input type="checkbox"/> BG Bulgaria | <input type="checkbox"/> KE Kenya | <input type="checkbox"/> SD Sudan |
| <input type="checkbox"/> BR Brazil | <input type="checkbox"/> KG Kyrgyzstan | <input type="checkbox"/> SE Sweden |
| <input type="checkbox"/> BY Belarus | <input type="checkbox"/> KP Democratic People's Republic of Korea | <input type="checkbox"/> SG Singapore |
| <input type="checkbox"/> BZ Belize | | <input type="checkbox"/> SI Slovenia |
| <input type="checkbox"/> CA Canada | <input type="checkbox"/> KR Republic of Korea | <input type="checkbox"/> SK Slovakia |
| <input type="checkbox"/> CH & LI Switzerland and Liechtenstein | <input type="checkbox"/> KZ Kazakhstan | <input type="checkbox"/> SL Sierra Leone |
| <input type="checkbox"/> CN China | <input type="checkbox"/> LC Saint Lucia | <input type="checkbox"/> TJ Tajikistan |
| <input type="checkbox"/> CO Colombia | <input type="checkbox"/> LK Sri Lanka | <input type="checkbox"/> TM Turkmenistan |
| <input type="checkbox"/> CR Costa Rica | <input type="checkbox"/> LR Liberia | <input type="checkbox"/> TR Turkey |
| <input type="checkbox"/> CU Cuba | <input type="checkbox"/> LS Lesotho | <input type="checkbox"/> TT Trinidad and Tobago |
| <input type="checkbox"/> CZ Czech Republic | <input type="checkbox"/> LT Lithuania | |
| <input type="checkbox"/> DE Germany | <input type="checkbox"/> LU Luxembourg | <input type="checkbox"/> TZ United Republic of Tanzania |
| <input type="checkbox"/> DK Denmark | <input type="checkbox"/> LV Latvia | <input type="checkbox"/> UA Ukraine |
| <input type="checkbox"/> DM Dominica | <input type="checkbox"/> MA Morocco | <input type="checkbox"/> UG Uganda |
| <input type="checkbox"/> DZ Algeria | <input type="checkbox"/> MD Republic of Moldova | <input checked="" type="checkbox"/> US United States of America |
| <input type="checkbox"/> EE Estonia | | <input type="checkbox"/> UZ Uzbekistan |
| <input type="checkbox"/> ES Spain | <input type="checkbox"/> MG Madagascar | <input type="checkbox"/> VN Viet Nam |
| <input type="checkbox"/> FI Finland | <input type="checkbox"/> MK The former Yugoslav Republic of Macedonia | <input type="checkbox"/> YU Yugoslavia |
| <input checked="" type="checkbox"/> GB United Kingdom | <input type="checkbox"/> MN Mongolia | <input type="checkbox"/> ZA South Africa |
| <input type="checkbox"/> GD Grenada | | <input type="checkbox"/> ZW Zimbabwe |

Check-boxes below reserved for designating States which have become party to the PCT after issuance of this sheet:

- | | | |
|--------------------------------|--------------------------------|--------------------------------|
| <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> |
| <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> |

Precautionary Designation Statement: In addition to the designations made above, the applicant also makes under Rule 4.9(b) all other designations which would be permitted under the PCT except any designation(s) indicated in the Supplemental Box as being excluded from the scope of this statement. The applicant declares that those additional designations are subject to confirmation and that any designation which is not confirmed before the expiration of 15 months from the priority date is to be regarded as withdrawn by the applicant at the expiration of that time limit. (Confirmation (including fees) must reach the receiving Office within the 15-month time limit.)

Box No. VI PRIORITY CLAIM

priority of the following earlier application(s) is hereby claimed:

Filing date of earlier application (day/month/year)	Number of earlier application	Where earlier application is:		
		national application: country	regional application:* regional Office	international application: receiving Office
item (1) 10 March 2001 (10.03.01)	0105975.7	GB		
item (2)				
item (3)				
item (4)				
item (5)				

☐ Further priority claims are indicated in the Supplemental Box.

The receiving Office is requested to prepare and transmit to the International Bureau a certified copy of the earlier application(s) (only if the earlier application was filed with the Office which for the purposes of this international application is the receiving Office) identified above as:

☐ all items ☒ item (1) ☐ item (2) ☐ item (3) ☐ item (4) ☐ item (5) ☐ other, see Supplemental Box

* Where the earlier application is an ARIPO application, indicate at least one country party to the Paris Convention for the Protection of Industrial Property or one Member of the World Trade Organization for which that earlier application was filed (Rule 4.10(b)(ii)):

Box No. VII INTERNATIONAL SEARCHING AUTHORITY

Choice of International Searching Authority (ISA) (if two or more International Searching Authorities are competent to carry out the international search, indicate the Authority chosen; the two-letter code may be used):

ISA /

Request to use results of earlier search; reference to that search (if an earlier search has been carried out by or requested from the International Searching Authority):

Date (day/month/year)

Number

Country (or regional Office)


Box No. VIII DECLARATIONS

The following declarations are contained in Boxes Nos. VIII (i) to (v) (mark the applicable check-boxes below and indicate in the right column the number of each type of declaration):

Number of
declarations

- | | | |
|---|--|---|
| <input type="checkbox"/> Box No. VIII (i) | Declaration as to the identity of the inventor | : |
| <input type="checkbox"/> Box No. VIII (ii) | Declaration as to the applicant's entitlement, as at the international filing date, to apply for and be granted a patent | : |
| <input type="checkbox"/> Box No. VIII (iii) | Declaration as to the applicant's entitlement, as at the international filing date, to claim the priority of the earlier application | : |
| <input type="checkbox"/> Box No. VIII (iv) | Declaration of inventorship (only for the purposes of the designation of the United States of America) | : |
| <input type="checkbox"/> Box No. VIII (v) | Declaration as to non-prejudicial disclosures or exceptions to lack of novelty | : |

CHECK LIST; LANGUAGE OF FILING

International application contains: following number of sheets in paper form: request (including declaration sheets) : 4 description (excluding sequence listing part) : 11 claims : 2 abstract : 1 drawings : 5 Sub-total number of sheets : 23 sequence listing part of description (actual number of sheets if filed in paper form, whether or not also filed in computer readable form; see (b) below) : Total number of sheets : 23 (b) sequence listing part of description filed in computer readable form (i) <input type="checkbox"/> only (under Section 801(a)(i)) (ii) <input type="checkbox"/> in addition to being filed in paper form (under Section 801(a)(ii)) Type and number of carriers (diskette, CD-ROM, CD-R or other) on which the sequence listing part is contained (additional copies to be indicated under item 9(ii), in right column):	This international application is accompanied by the following item(s) (mark the applicable check-boxes below and indicate in right column the number of each item): 1. <input checked="" type="checkbox"/> fee calculation sheet : 2. <input type="checkbox"/> original separate power of attorney : 3. <input checked="" type="checkbox"/> original general power of attorney : 4. <input type="checkbox"/> copy of general power of attorney; reference number, if any: : 5. <input type="checkbox"/> statement explaining lack of signature : 6. <input type="checkbox"/> priority document(s) identified in Box No. VI as item(s): : 7. <input type="checkbox"/> translation of international application into (language): : 8. <input type="checkbox"/> separate indications concerning deposited microorganism or other biological material : 9. <input type="checkbox"/> sequence listing in computer readable form (indicate also type and number of carriers (diskette, CD-ROM, CD-R or other)) : (i) <input type="checkbox"/> copy submitted for the purposes of international search under Rule 13ter only (and not as part of the international application) : (ii) <input type="checkbox"/> (only where check-box (b)(i) or (b)(ii) is marked in left column) additional copies including, where applicable, the copy for the purposes of international search under Rule 13ter : (iii) <input type="checkbox"/> together with relevant statement as to the identity of the copy or copies with the sequence listing part mentioned in left column : 10. <input checked="" type="checkbox"/> other (specify): Patents. Form 23/77..... :	Number of items
Figure of the drawings which should accompany the abstract: 1a	Language of filing of the international application: English	
Box No. X SIGNATURE OF APPLICANT, AGENT OR COMMON REPRESENTATIVE		
Next to each signature, indicate the name of the person signing and the capacity in which the person signs (if such capacity is not obvious from reading the request).		
<div style="text-align: center;">  SHARP Alan Cooper - ON BEHALF OF QED I.P. SERVICES LIMITED Authorised Representative for Central Research Laboratories Limited LITTLE Max Andrew </div>		

For receiving Office use only		
1. Date of actual receipt of the purported international application:	06 MARCH 2002 06.03.2002	2. Drawings:
3. Corrected date of actual receipt due to later but timely received papers or drawings completing the purported international application:		<input checked="" type="checkbox"/> received:
4. Date of timely receipt of the required corrections under PCT Article 11(2):		<input type="checkbox"/> not received:
5. International Searching Authority (if two or more are competent): ISA /	6. <input checked="" type="checkbox"/> Transmittal of search copy delayed until search fee is paid	

For International Bureau use only
Date of receipt of the record copy by the International Bureau:

A METHOD OF MODIFYING LOW FREQUENCY COMPONENTS OF A DIGITAL AUDIO SIGNAL

5

The present invention relates to a method of modifying low frequency components of a digital audio signal.

When music is performed live using large public address loudspeakers, low-frequency
10 vibrations (below approximately 50 Hz) are generated. These low frequency vibrations travel through the floor and are mechanically coupled to listeners in the audience, causing them to sense the vibrations through their feet and also within the chest cavity. Engineers in recording studios, when mixing music, must create a musical balance such that all frequency ranges (low, mid and high) can be reproduced on a wide range of
15 loudspeakers. When this mixed music is listened to at home, or in another setting, it is likely to be using much smaller loudspeakers than those used for live performances. These smaller loudspeakers are often inadequate at reproducing low (i.e., bass) frequencies, and this sometimes leads to a degradation in the quality of the listening experience. This problem has been addressed by using methods of enhancing the low
20 frequency parts of an audio signal so that the quality of the music when played over small loudspeakers is improved.

A method for digitally modifying low frequency components of audio signals should satisfy the following design constraints:

- music processed using the method should not sound unpleasant (constraint *c1*);
- 25 • the method should not noticeably alter the tonal character of musical instruments (constraint *c2*);
- the method should also not noticeably affect high frequency signals (constraint *c3*);
- the method should not alter the balance of left and right channels of the stereo signal (constraint *c4*);
- 30 • the method should not be prohibitively complex (constraint *c5*);

- the method must not cause the maximum signal level of the digital system to be exceeded (constraint c6); and
- the method must not amplify or introduce very low frequency signals that cannot be reproduced by small loudspeakers (constraint c7).

5

In digital signal processing, it is essential that the maximum signal level (i.e., unity) of the audio signal is never exceeded, otherwise extreme audible artefacts can result. For example, considering a 16-bit audio signal, the range of signal values is $-32,768$ to $+32,767$ (i.e., 2^{16} different values). If the signal value exceeds $+32,767$ then the signal value overflows to $-32,768$ rather than to its next highest value of $+32,768$. This creates extreme artefacts in the audio signal, and it is therefore vital to ensure that the maximum signal limits are never exceeded. In analogue systems this type of signal overflow does not occur on account of the operating tolerances of devices such as valves, diodes, capacitors, transistors and resistors.

Low frequency audio signals may be enhanced using a number of techniques, some of which will now be discussed. One method of enhancing such signals is by the use of equalisation wherein either one or many filters with different gain values process the signal, and lower frequency signals are given higher gain values. Thus low frequencies (and hence bass instruments) are emphasised by virtue of the fact that lower frequency energy is amplified. However, since most of the signal energy in a musical audio signal is concentrated into the lower frequencies this technique cannot amplify the low frequency signals very much before the maximum signal level in the system is exceeded, or the music sounds distorted. This method therefore breaks constraints c6 and c7.

Multi-band compression is another technique that may be used to enhance bass frequencies. In this technique one or many filters are arranged in parallel, as in equalisation. The output of each filter is processed by a dynamic compressor that measures the current signal level in that frequency band and applies a gain whose amount is related to that measurement. The signal energy in each frequency band is averaged over time and the compressors are arranged to operate such that the bass

frequency bands are kept at a higher average energy than the higher frequency bands. Bass instruments (such as bass drums, guitars etc) are therefore emphasised because the signal energy is higher on average in the lower frequency bands than in the higher frequency bands. However, since the gain of each band is independent of other bands, a musical instrument will often be noticeably tonally changed since the fundamental and harmonics of a note often falls across many frequency bands. This method therefore breaks constraint c2.

A device which uses a method similar to multi-band compression is disclosed in US Patent No. 5,359,665 (Aphex Systems Ltd). This device is an analogue device which combines phase inverted, dynamically compressed bass frequencies with the original audio signal. It provides greater enhancement of the bass frequencies when they are at lower levels and less enhancement when they are at higher levels, thereby satisfying constraint c6. However, the device is not designed to work with stereo signals: if the device is used for the left and right channels of a stereo signal, the musical image will drift from side to side as the left and right gain factors are independent of one another. This breaks constraint c4. The device also does not employ a very low frequency cut-off filter that would prevent the breaking of constraint c7. For very small loudspeakers, this device would not be able to reproduce maximum level signals.

Published International Patent Application No. WO-A1-9846044 (K.S. Waves Ltd) describes an apparatus and method for bass enhancement. The method uses the psycho-acoustic principle of virtual pitch, in which the pitch of a musical note is recognised by the frequency spacing and relative level of the harmonics of the fundamental of that note. The method involves taking a certain range of bass frequencies and generating artificial harmonics of these frequencies which are at a higher frequency than the fundamental bass frequencies. The original bass frequencies are not actually present in the processed signal, only the artificial harmonics, as the fundamental does not need to be present for the pitch to be recognisable. However, audio signals which are processed using this method can be musically unpleasant as, for the effect to be noticeable, frequencies in the range 100 to 300 Hz must be quite loud. This breaks constraint c1. Also, the apparatus has many functional components and higher-order statistical processing which breaks constraint c5.

An aim of the present invention is to provide a method for modifying (i.e., enhancing) low frequency components (i.e., from ~40 to ~150 Hz) of a digital audio signal. Another aim of the present invention is to provide a method for modifying low frequency components of a digital audio signal so that the signal is suitable for playing over small
5 loudspeakers. A further aim of the invention is to provide a method for modifying low frequency components of a digital audio signal which does not violate the constraints *c1* to *c7*.

According to the first aspect of the invention there is provided a method of modifying low frequency components of a digital audio signal as specified in the claims, and the
10 product thereof.

According to a further aspect of the invention there is provided a computer program for implementing the method claimed.

An embodiment of the invention will now be described, by way of example only, with reference to the accompanying Figures, in which:-

15 Figure 1a shows a system diagram of the main method steps;

Figure 1b shows a system diagram of a limiter used in the method;

Figure 1c shows the output of a peak-hold circuit;

Figure 1d shows the limiter input-output characteristics; and

Figure 2 shows a combined plot of the frequency-gain characteristics of the high-pass
20 and the band-pass filters.

Referring to Figure 1a, the first step of the method of the invention involves splitting the left (12) and right (14) channels of a digital audio signal (10) into two separate, identical signals to give a first (12a) and second (12b) left audio signal, and a first (14a) and second (14b) right audio signal. The first left (12a) and right (14a) audio signals are
25 filtered by left (16) and right (20) high-pass filters, respectively. The left (16) and right (20) high-pass filters have the same filter characteristics.

The second left (12b) and right (14b) audio signals are passed through left (18) and right (22) band-pass filters, respectively. The left (18) and right (22) band-pass filters have the same filter characteristics. The band-pass filters (18,22) are designed so that they completely attenuate frequencies below a certain frequency, depending on the type of loudspeakers on which the processed audio signal is to be played. The frequency-gain characteristics of the digital band-pass filters (18,22) for use with hi-fi speakers are shown in Figure 2. It is the relationship between the gain and the frequency of the band-pass filters (18,22) that partly determines whether the constraints $c1$ to $c7$ are satisfied. It is noticeable that below the minimum frequency range of the speakers (i.e., ~50 Hz for hi-fi speakers), the band-pass filter is designed to attenuate dramatically.

The band-pass filters (18,22) can be implemented as standard Butterworth infinite impulse response (IIR) filters, but the parameters of the filters depend upon the loudspeakers that the processed signal is to be played over. Table 1 below shows the design parameters for the band-pass filters (18,22) for different types of loudspeakers, where $fs1$ is the lower cut-off frequency, $fs2$ is the upper cut-off frequency, $fp1$ is the lower pass-band frequency, $fp2$ is the upper pass-band frequency, Ap is the pass-band ripple and As is the stop-band ripple.

Speaker Type	Lowest Frequency (Hz)	Butterworth Design Parameters $fs1, fp1, fp2, fs2$ (Hz), Ap, As (dB)
Notebook PC	100	80, 100, 150, 180, 8, 11
Multimedia PC	80	50, 80, 120, 150, 8, 11
Hi-Fi	50	20, 50, 120, 150, 8, 11

Table 1

It is essential that the method of the invention enhances only those frequencies that can be reproduced by the loudspeakers on which the audio signal is to be played. Very low frequency signals which are below the reproduction range of small loudspeakers must therefore be removed. The amount of attenuation of these very low frequency signals is dependent upon the size of the loudspeaker, thereby ensuring that constraint $c7$ is not broken.

The frequency-gain characteristics of the high-pass filters (16,20) are shown in Figure 2. These filters are also implemented as Butterworth IIR filters and, again, the parameters of the filters depend upon the size of the loudspeakers that the signal is to be played over. Table 2 shows the design parameters for the high-pass filters (16,20) for different types of loudspeakers, where f_s is the stop-band frequency, f_p is the pass-band frequency, A_p is the pass-band ripple, and A_s is the stop-band ripple.

Speaker Type	Butterworth Design Parameters
	f_s, f_p (Hz), A_p, A_s (dB)
Notebook PC	160, 190, 8, 14
Multimedia PC	140, 170, 8, 14
Hi-Fi	140, 170, 8, 14

Table 2

The high-pass (16,20) and band-pass (18,22) filters divide each channel (12,14) of the stereo audio signal (10) into two separate frequency regions: a mid to high frequency region, and a low frequency region, respectively. The high-pass filters (16,20) have an attenuation of -0.8 dB for the mid- and high-range frequencies. This has the effect of shifting the attention of the listener so that the bass frequencies/instruments become more noticeable without breaking the constraints $c1$ to $c7$.

In the next step of the method, the absolute magnitudes of the outputs of the left (18) and right (22) band-pass filters are determined, and the signal with the largest amplitude

is taken to be the control signal (28). This step is critical as it ensures that constraints $c4$ and $c6$ are not broken.

A level control circuit for low and medium sound is disclosed in US Patent No. 5,175,770 (Samsung). In this circuit, the left (12) and right (14) signals are added together using an adder before the main processing steps in the circuit are carried out. However, the difficulty with this approach is that if the signal level in both the left and right input channels is larger than one half of the maximum signal amplitude, then the signal level at the output of the adder will be greater than unity, breaking constraint $c6$. It can be demonstrated that in a good deal of music, common-mode signals (i.e., those signals that appear with equal amplitude in both left and right channels) are indeed extremely likely to exceed half the maximum system amplitude. This is a significant problem for fixed-point digital arithmetic.

The methods disclosed in US Patents Nos. 4,182,930 (DBX Inc.) and 4,982,435 (Sanyo) both take a sum combination of the left and right input signals thereby creating a mono bass signal that is level adjusted and added back to the left and right input signals. The problem with this approach is that it typically affects the stereo image of the bass signals in the music, thus breaking constraint $c4$.

In the next step of the method of the invention, the control signal (28) with the largest amplitude (either positive or negative), is then passed to a limiter (34). The purpose of the limiter (34) is to limit the dynamic range of the largest control signal (28) to below the limiter threshold value T_l , and then to amplify the limited signal to increase its energy. In this way, the 0 dB level (i.e., constraint $c6$) is not exceeded, but the signal energy is amplified. The detailed operation of the limiter (34) is illustrated by the circuit shown in Figure 1b although, in practice, the limiting function is carried out digitally.

The limiter (34) includes a peak-hold circuit (36), the typical output of which is shown by the dashed line in Figure 1c. This peak-hold circuit functions by efficiently calculating the L_∞ norm of the control signal (28) whose samples have been weighted according to an exponentially decaying envelope. The circuit function is described by the following operation:

$$y(t) = \left\| x(t-n) \left(K_p \right)^n \right\|_{\infty}$$

where t is the current time sample, n is the index of the normal ($n \in 0 \dots \infty$), $y(t)$ is the current peak-hold sample, $x(t)$ is the current peak-hold input sample, and K_p is the decay coefficient. This operation smoothly tracks the peaks of the control signal (28) as they decay under the influence of the exponential envelope.

It is important that the decay time of the circuit (36) is set so that it accurately follows the amplitude of the control signal (and therefore the bass frequencies). It is also important that the circuit (36) does not clip wave peaks or hold for an excessive amount of time after the signal level of the bass frequencies has died away. The decay time of the peak-hold circuit (36) depends solely upon the decay coefficient, K_p , and the sample rate S . The impulse response of the peak-hold circuit in decay mode is given by:

$$h(n) = \left(K_p \right)^n, \text{ where } K_p = \exp \left(\frac{\ln(10^{-6})}{S \cdot T_p} \right), \text{ and } T_p \text{ is the required delay time of the}$$

peak-hold circuit, in seconds. The decay time is then the time taken for the peak-hold circuit to reach 1 millionth of the original amplitude. The optimum setting for T_p was found to be $0.3 (\pm 5\%)$ seconds.

The output signal from the peak-hold circuit (36) is then filtered by a smoothing filter (38) which comprises a digital low-pass filter. It is important that the response of the smoothing filter (38) is set so that sharp peaks captured by the peak-hold circuit (36) are smoothed to prevent clicks in the processed output audio signal. As the smoothing filter (38) is a simple one pole low-pass filter, the feedback coefficient, K_s , is calculated as for the peak-hold circuit. Experimentation has revealed an optimum decay time, T_s , for the smoothing filter (38) of 0.05 seconds. The Z-transform of the transfer function of the smoothing filter is given by: $H(z) = \frac{1 - K_s}{1 - K_s \cdot z^{-1}}$ from which it can be seen that the smoothing filter (38) is normalised to have unity gain at 0 Hz. This is implemented as a standard difference equation for digital implementation.

Due to the complex relationship between the decay time of the peak-hold circuit (36) and the transient response of the smoothing filter (38), the smoothing filter takes some time to respond to peaks from the peak-hold circuit. As a result, there are moments when the output signal energy is larger than unity, breaking constraint c6. To
 5 compensate for this, a small headroom attenuation H_r is subtracted from the control signal. For reasons of computational efficiency, the headroom attenuation is subtracted from the control signal in the following method step.

In the next step of the method, the amplitude of the output (100) of the smoothing filter
 10 (38) is adjusted. In analogue terms this is carried out using an amplitude adjustment circuit which comprises a divider (42), a comparator (40), and a switch (44). The comparator (40) 'informs' the switch (44) whether to select either 1) a post-gain constant, P_g , in the case where the smoothing filter output (100) is less than or equal to the threshold level T_l , or 2) a headroom compensated gain, G_c , divided by the
 15 smoothing filter output (38) if the smoothing filter output (38) is more than the threshold level.

Figure 1d shows that the effect of the amplitude adjustment circuit is to amplify the control signals that are between zero and the threshold level by a large, fixed amount,
 20 and to amplify control signals above the threshold level in a quantity inversely proportional to that level. The nature of the decreasing slope of the graph of Figure 1d is such that when the smoothing filter output (100) is equal to the headroom compensated gain G_c , the control signal energy is unchanged, and when the smoothing filter output is unity (representing 0dB), the control signal energy is attenuated by the headroom level
 25 H_r . In other words, Figure 1d shows that when the amplitude of the bass frequency signals is very small, the bass frequencies are amplified by a large amount. When the amplitude of the bass frequencies is very large, they are attenuated by a small amount (i.e., the headroom value). There is, however, an equilibrium point at intermediate amplitude, when the bass frequencies are unchanged.

As mentioned previously, for reasons of computational efficiency the headroom attenuation is implemented by combining the headroom value with the parameters G_c and P_g in the amplitude adjustment circuit. In practice, the headroom attenuation H_r is set to 3.0 dB ($\pm 5\%$), although this may be adjusted depending on the type of music which is to be processed. The following three equations are used to obtain the linear values for the post-gain level P_g , the threshold level T_l , and the headroom compensated gain G_c :

$$P_g = 10^{0.1|-T_{ld}-H_{rd}|} ; \quad T_l = 10^{0.1T_{ld}} ; \quad G_c = T_l P_g ;$$

where T_{ld} is the negative threshold level in dB, and H_{rd} is the positive headroom level in dB.

The limiter output control signal (30) is then used to vary the amplitude of the left (46) and right (48) output signals of the band-pass filters (18,22) to give modified left (50) and right (52) band-pass filtered signals. The modified left (50) and right (52) band-pass filtered signals are then recombined with the left (54) and right (56) high-pass filtered signals, respectively, giving the bass enhanced left (58) and right (60) audio output signals.

The parameter which affects the degree to which the method of the invention satisfies constraint c2 is the limiter threshold level T_l . In choosing the limiter threshold, care must be taken to avoid tonal alteration of the processed signal. Tonal alteration results when the relative balance of low to high-order harmonics of an instrument are affected differently, depending upon whether they fall inside or outside the bass limiter frequency range (i.e., the range of the band-pass filter). It has been found experimentally that a threshold level T_l of -14 dB ($\pm 5\%$) provides an optimum balance between maximum bass enhancement and minimum tonal alteration.

As the digital audio signal (10) consists of a large number of discrete samples, each step of the method is applied to every discrete sample in turn. For example, the step of calculating the absolute magnitude of the outputs of the left (18) and right (22) band-pass filters in order to find the control signal (28) is carried out on each discrete sample.

This means that the control signal (28) may be formed from the left channel in one sample, but from the right channel in the subsequent sample.

Variation may be made to the aforementioned embodiment without departing from the scope of the invention. For example, the method is also suitable for use with
5 headphones. As headphones often have radically different frequency responses, it is possible to modify the design frequencies for the band-pass and high-pass filters such that the method can be matched to specific types of headphones such as in-ear, open or closed back headphones.

Different types of music have different dynamic characteristics. For example, dance
10 music often has fast, staccato bass notes, and classical music has long, slow decaying notes. It is possible to provide a preset user control of parameters such as the decay coefficients K_p and K_s . The user could then select the type of music they are listening to, and have the parameters downloaded from a preset table. These parameters may be derived experimentally for different types of music or, in a further variation to the
15 invention, higher-order statistical measurement of the dynamics of the music could allow automatic adjustment of the control parameters T_l , K_p and K_s , based on an adaptive, midterm statistical measure. In addition, the parameters of the high-pass (16,20) and/or band-pass (18,22) filters may be user selectable – parameters such as the cut-off frequency, pass-band frequency, pass-band ripple and stop-band ripple.

20 In a further variation, the precise mathematical relationship between the control signal greater-than-unity excursions and the peak-hold and smoothing decay times could be formulated, rather than being determined experimentally. This would allow automatic setting of the gain restoration headroom parameter, which may need to be altered if the device were to have user presets for different types of music, or if higher-order
25 statistical processing has been used.

CLAIMS

1. A method of modifying low frequency components of a digital audio signal (10) having left (12) and right (14) channel signals, the method comprising the steps of: a) filtering the left (12) and right (14) channels signals using respective left (16) and right (20) high-pass filters to form left (54) and right (56) high-pass filtered signals; b) filtering the left (12) and right (14) channel signals using respective left (18) and right (22) band-pass filters to form left (46) and right (48) low frequency signals; c) modifying the amplitude of the left (46) and right (48) low frequency signals to give modified left (50) and right (52) low frequency signals, whereby signals (46,48) with amplitude a where $0 < a \leq a1$ are amplified by a first constant value $C1$, signals (46,48) with amplitude $a1 \leq a < a2$ are amplified proportional to $1/a$, signals (46,48) with amplitude $a = a2$ are unchanged, signals (46,48) with amplitude $a2 < a < a3$ are attenuated proportional to $1/a$, and signals (46,48) with amplitude $a = a3$ are attenuated by a second constant value $C2$; and d) combining the modified band-pass filtered left (50) and right (52) signals with the respective left (54) and right (56) high-pass filtered signals to form respective modified left (58) and right (60) channel audio signals.
2. A method according to claim 1 wherein in step c), the amplitude a of the signal is taken to be the amplitude of the left (46) or right (48) low frequency signal which has the largest absolute value.
3. A method according to claim 2 wherein the first constant value $C1$ is 12.5.
4. A method according to any preceding claim wherein the second constant value $C2$ is 0.5.
5. A method according to any preceding claim wherein $a1 = 0.04$.
6. A method according to any preceding claim wherein $a2 = 0.5$.
7. A method according to any preceding claim wherein $a3 = 1$.

8. A method according to any preceding claim wherein the digital audio signal (10) is an MP3 encoded signal.
9. A method according to any preceding claim wherein the digital audio signal (10) is in WAV format.
- 5 10. A method according to any preceding claim wherein the parameters of the band-pass filters (18,22) are user selectable.
11. A method according to any preceding claim wherein the parameters of the high-pass filters (16,20) are user selectable.
12. A method claimed in any of claims 1 to 11 using a limiter (34) having a transfer
10 function substantially as shown in Figure 1d.
13. A digital signal produced using the method claimed in any of claims 1 to 12.

ABSTRACT

**A METHOD OF MODIFYING LOW FREQUENCY COMPONENTS
OF A DIGITAL AUDIO SIGNAL**

5

A method of enhancing low frequency components of a digital audio signal (10) having left (12) and right (14) channel signals, comprises: a) filtering the left (12) and right (14) channels signals using respective left (16) and right (20) high-pass filters to form left (54) and right (56) high-pass filtered signals; b) filtering the left (12) and right (14) channel signals using respective left (18) and right (22) band-pass filters to form left (46) and right (48) low frequency signals; c) modifying the amplitude of the left (46) and right (48) low frequency signals to give modified left (50) and right (52) low frequency signals, whereby signals (46,48) with amplitude a where $0 < a \leq a1$ are amplified by a first constant value $C1$, signals (46,48) with amplitude $a1 \leq a < a2$ are amplified proportional to $1/a$, signals (46,48) with amplitude $a = a2$ are unchanged, signals (46,48) with amplitude $a2 < a < a3$ are attenuated proportional to $1/a$, and signals (46,48) with amplitude $a = a3$ are attenuated by a second constant value $C2$; and d) combining the modified band-pass filtered left (50) and right (52) signals with the respective left (54) and right (56) high-pass filtered signals to form respective modified left (58) and right (60) channel audio signals. The method has the advantage that the maximum signal level (i.e., unity) of the audio signal is never exceeded, thus avoiding extreme audible artefacts.

(Figure 1 a)

25

Figure 1a

PCT/GB 02 / 00987




Figure 1b




Figure 1c




Figure 1d




Figure 2

